



VHF AND UHF TRANSCEIVERS

IC-F3161DT

(IDAS digital VHF transceiver with 10-keypad)

IC-F3161T

(VHF transceiver with 10-keypad)

IC-F3161DS

(IDAS digital VHF transceiver without 10-keypad)

IC-F3161S

(VHF transceiver without 10-keypad)

IC-F4161DT

(IDAS digital UHF transceiver with 10-keypad)

IC-F4161T

(UHF transceiver with 10-keypad)

IC-F4161DS

(IDAS digital UHF transceiver without 10-keypad)

IC-F4161S

(UHF transceiver without 10-keypad)



INTRINSICALLY SAFE VERSION



Conventional/IDAS™ Digital/IDAS™ Trunking Multi-Mode Land Mobile!



▲ IC-F3161DT/T

▲ IC-F4161DS/S

IP55 dust-protection and water jet resistance

The IC-F3161/D series meets IP55 requirements for dust-protection and water jet resistance. Its durable construction is backed up by the aluminum die-cast chassis and polycarbonate casing, allowing reliable operation under harsh weather and environmental conditions.

Lithium-Ion battery pack

The supplied 2000mAh (typ.) Li-Ion battery pack, BP-232FM, provides 14 hours* of operating time.

* Typical operation Tx:Rx:Stand-by=5:5:90, power save on

Most popular signalings built-in

The 2-Tone, 5-Tone, CTCSS, DTCS and MDC signaling capabilities are built-in for group communication or selective calling. The radio can decode ten 2-Tone codes or eight 5-Tone codes on a channel. When a matched tone is received, the following actions are programmable for each code.

- Beep sound
- Answer back call
- Radio stun/kill/revive
- Bell icon
- Auto TX
- Scan

Basic LTR™ /conventional mode operation

Both LTR™ trunking and conventional channels are programmable on a radio. Group, selective (DTMF), and phone call are available in LTR™ mode.

MDC 1200 Compatible

The following selective calling and ANI features are available with the built-in MDC signaling.

- PTT ID
- Radio check
- Radio stun/revive
- 500 Aliases
- Status message/request
- Call alert
- Emergency, emergency mic monitoring

Voting mode scanning

The voting mode scanning detects the signal strength level of repeater stations and automatically selects the strongest station, useful for roaming between 2 or more repeater sites. Once you program the voting mode to a memory zone, you can easily start voting mode operation by changing the zone setting.

VHF TRANSCEIVERS

IC-F3161DT/T

IDAS digital/analog FM with 10-keypad

IC-F3161DS/S

IDAS digital/analog FM without 10-keypad

UHF TRANSCEIVERS

IC-F4161DT/T

IDAS digital/analog FM with 10-keypad

IC-F4161DS/S

IDAS digital/analog FM without 10-keypad

* IC-F3161/F4161 "D" versions only.

Full dot-matrix LCD

Using a large full dot-matrix LCD (32 × 18 mm), the IC-F3161/D series shows upper and lower case characters clearly. The display setting is selectable from 1 line, 12 characters or 2 lines 24 characters via programming. The bottom row shows assigned functions to the [P0] to [P3] buttons.



Enhanced audio

The IC-F3161/D series employs a BTL amplifier that increases the audio output and the built-in audio compander provides clear, low noise communications.

Lone worker function

When the radio is not operated for a preset period, a beep sounds and a button push is required. If no button is pushed within that preset time, an emergency signal automatically transmits and alerts your co-worker or dispatcher to any potential trouble.

Intrinsically safe

The Intrinsically safe version is approved by the FM Approvals. It is suitable for use in hazardous areas where flammable gasses or liquids are used.

See specification page for applied classes.

Other features

- 512 memory channel with 128 zones
- 8 DTMF autodial memories
- Built-in inversion type voice scrambler
- 2 step reduced power setting
- Busy, repeater lockout functions
- Escalating alarm
- Mode dependent scan
- Surveillance function temporarily turns off the LED backlight and beep sound
- Powerful 5W output both in VHF and UHF
- Flash CPU for future upgrade and more...

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.

BATTERY PACK



BP-232FM

Battery pack	Voltage	Capacity	Battery life*
BP-232FM	7.4V (Li-Ion)	1900mAh (min.) 2000mAh (typ.)	14 hours

*1 Operating time is approximate time (at 20°C). 5:5:90 duty cycle with power save on.

Do not charge the BP-232FM in an explosive atmosphere.

REGULAR CHARGER



BC-147SA BC-171

BC-171 DESKTOP CHARGER + BC-147SA AC ADAPTER
Charging time: 10 hours (approx.).

RAPID CHARGER



BC-145SA BC-160

BC-160 DESKTOP CHARGER + BC-145SA AC ADAPTER
Charging time: 3 hours (approx.).

RAPID CHARGER



AD-106 BC-145SA BC-119N

BC-119N DESKTOP CHARGER + AD-106 CHARGER ADAPTER + BC-145SA AC ADAPTER
Charging time: 3 hours (approx.).

MULTI-CHARGER



BC-121N+AD-106 (6 pcs.)

BC-121N MULTI-CHARGER + AD-106 CHARGER ADAPTER + BC-157S AC ADAPTER
Rapidly charges up to 6 battery packs (Six AD-106s are required). Charging time: 3 hours (approx.).

DC POWER CABLE



BC-157S

DC POWER CABLE



OPC-656

OPC-656: For use with the BC-121N. (12–20V DC required).


SPEAKER-MICROPHONE



IPX7 HM-169IS

HM-169IS: Speaker-microphone. Equivalent to IP57.

HEADSETS AND PTT/VOX CASE



HS-94 HS-95 HS-97 VS-1SC

HS-94: Earhook headset with flexible boom microphone.
HS-95: Behind-the-head headset with flexible boom microphone.
HS-97: Throat microphone fits around your neck and picks up speech vibration.
VS-1SC: PTT/VOX case. Required when using these headsets.

BELT CLIPS



MB-93 MB-94

MB-93: Swivel type. Prevents accidental dropping from your belt.
MB-94: Alligator type. Same as supplied.

LEATHER BELT HANGERS



MB-96N MB-96F

MB-96N: Swivel type belt hanger.
MB-96F: Fixed type belt hanger. For use with MB-94.

ANTENNAS

- **FA-SC25V** : 136–150MHz
- **FA-SC55V** : 150–174MHz
- **FA-SC25U** : 400–430MHz
- **FA-SC57U** : 430–470MHz
- **FA-SC72U** : 470–520MHz

CUT ANTENNAS

- **FA-SC61VC** : 136–174MHz
- **FA-SC61UC** : 380–520MHz

Cut the antenna element to tune to a specific center frequency.

IDAS™ digital mode ready*

DIGITAL

The IDAS (Icom Digital Advanced System) is Icom's digital conventional and trunking system based on the NXDN™ common air interface. It has useful calling features including selective calling, status message, radio stun/kill/revive, etc.

* The IC-F3161DT/DS, F4161DT/DS "D" versions only. See the IDAS brochure for details.

SPECIFICATIONS

GENERAL

- Frequency range :
 - IC-F3161T/S, DT/DS 136–174MHz
 - IC-F4161T/S, DT/DS 400–470MHz, 450–512MHz
- Number of channels : 512 channels/128 zones
- Channel spacing : 12.5kHz/25kHz, 15kHz/30kHz, 6.25kHz ("D" version only)
- Type of emission Wide : 16K0F3E, Narrow 11K0F3E, 11K0F7E, 11K0F7D 8K50F3E, 8K10F1E, 8K10F1D Digital ("D" version only) 4K00F1E, 4K00F1D
- Antenna impedance : 50Ω
- Usable temperature range : -20°C to +40°C; -4°F to +104°F
- Power supply requirement : 7.2V DC
- Current drain (at 7.2V DC; approx.):
 - Transmit VHF/UHF 1.5A/1.8A (at 5W/5W)
 - Receive stand-by 100mA ("D" version) 150mA/140mA (VHF/UHF) rated output 600mA
- Dimensions (with BP-232FM): 53 (W) × 136 (H) × 38.5 (D) mm; (projections are not included) 2³/₃₂ (W) × 5¹¹/₃₂ (H) × 1¹⁷/₃₂ (D) in
- Weight (approx.) : 340g; 12.0oz (with BP-232FM)

TRANSMITTER

- Output power VHF/UHF : 5W/2W/1W (Hi/L2/L1)
- Max. frequency deviation : ±5kHz (Wide), ±2.5kHz (Narrow)
- Frequency stability : ±1.0ppm
- Spurious emissions : 75dB typ.
- FM Hum and Noise : 46dB typ. (Wide), 40dB typ. (Narrow)
- Audio harmonic distortion : 3% typ. (AF 1kHz, 40% deviation)
- Modulation limiting : 60–100% of max. deviation
- Ext. microphone connector : 9-pin multi connector/ 2.2kΩ

Supplied accessories:

- Battery pack, BP-232FM
- Belt clip, MB-94
- Antenna (differs depending on version)

Measurements made in accordance with EIA-152C/204D, TIA-603 for analog. All stated specifications are subject to change without notice or obligation.

RECEIVER

- Sensitivity FM (W, N) : 0.25μV typ. (at 12dB SINAD) Digital : 0.20μV typ. (at 5% BER, "D" version only)
- Adjacent channel selectivity : 75dB typ. (Wide), 68dB typ. (Narrow)
- Spurious response : 70dB min.
- Intermodulation : 74dB typ.
- Hum and noise ratio : 46dB typ. (Wide), 40dB typ. (Narrow)
- Audio output power : 500mW typ. (at 5% distortion with an 8Ω load)
- External speaker connector : 9-pin multi connector/ 8Ω

Applicable U.S. Military Specifications & IP Rating

Icom makes rugged products that have been tested to and passed the following MIL-STD requirements and Ingress Protection standards.

Standard	MIL 810F	
	Method	Procedure
Low Pressure	500.4	I, II
High Temperature	501.4	I, II
Low Temperature	502.4	I, II
Temperature Shock	503.4	I
Solar Radiation	505.4	I
Rain Blowing/Drip	506.4	I, III
Humidity	507.4	–
Salt Fog	509.4	–
Dust Blowing	510.4	I
Vibration	514.5	I
Shock	516.5	I, IV

Also meets equivalent MIL-STD-810-C, -D and -E.

Ingress Protection Standard

Dust & Water	IP55 (Dust-protection and water jet resistance)
--------------	---

INTRINSICALLY SAFE



IC-F3161T/S, IC-F4161T/S

IS : Class I, II, III/ Div 1/ Groups CDEFG/ T3C Ta = 40°C

NI : Class I/ Div 2/ Groups ABCD/ T3C Ta = 40°C

IC-F3161DT/DS, IC-F4161DT/DS ("D" version)

(UT-126FM IDAS digital unit hardware installed)

IS : Class I, II, III/ Div 1/ Groups DEFG/ T3C Ta = 40°C

NI : Class I/ Div 2/ Groups ABCD/ T3C Ta = 40°C

Special condition for use

Must be used with the BP-232FM battery.

The HM-169IS, VS-1SC, HS-94, HS-95 and HS-97 are approved as intrinsically safe options. Any other options, except the antenna, belt clip and belt hanger, cannot be used in explosive atmosphere areas.

Never charge the BP-232FM (with/without the transceiver) in an explosive atmosphere. The optional battery chargers are not approved as intrinsically safe.

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia, Japan and/or other countries. IDAS and IDAS logo are trademarks of Icom Incorporated. NXDN is a trademark of Icom Incorporated and Kenwood Corporation. LTR is a trademark of E.F. Johnson Technologies Inc. All other trademarks are the properties of their respective holders.

Icom Inc.

1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

www.icom.co.jp/world

Count on us!

Icom America Inc.

2380 116th Avenue NE,
Bellevue, WA 98004, U.S.A.
Phone : +1 (425) 454-8155
Fax : +1 (425) 454-1509
E-mail : sales@icomamerica.com
URL : http://www.icomamerica.com

Icom Canada

Glenwood Centre #150-6165 Highway 17,
Delta, B.C., V4K 5B8, Canada
Phone : +1 (604) 952-4266
Fax : +1 (604) 952-0090
E-mail : info@icomcanada.com
URL : http://www.icomcanada.com

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone : +61 (03) 9549 7500
Fax : +61 (03) 9549 7505
E-mail : sales@icom.net.au
URL : http://www.icom.net.au

Icom New Zealand

146A Harris Road, East Tamaki,
Auckland, New Zealand
Phone : +64 (09) 274 4062
Fax : +64 (09) 274 4708
E-mail : inquiries@icom.co.nz
URL : http://www.icom.co.nz

Icom (Europe) GmbH

Communication Equipment
Auf der Krautweide 24
65812 Bad Soden am Taunus, Germany
Phone : +49 (6196) 76685-0
Fax : +49 (6196) 76685-50
E-mail : info@icom-europe.com
URL : http://www.icomeurope.com

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"
Bajos A 08174, Sant Cugat del Valles,
Barcelona, Spain
Phone : +34 (93) 590 26 70
Fax : +34 (93) 589 04 46
E-mail : icom@icomspain.com
URL : http://www.icomspain.com

Icom (UK) Ltd.

Blacksole House, Altrira Park,
Herne Bay, Kent, CT6 6GZ, U.K.
Phone : +44 (01227) 741741
Fax : +44 (01227) 741742
E-mail : info@icomuk.co.uk
URL : http://www.icomuk.co.uk

Icom France s.a.s.

Zac de la Plaine,
1 Rue Brindejonc des Moulinais, BP 45804,
31505 Toulouse Cedex 5, France
Phone : +33 (5) 61 36 03 03
Fax : +33 (5) 61 36 03 00
E-mail : icom@icom-france.com
URL : http://www.icom-france.com

Icom Polska

81-850 Sopot, ul. 3 Maja 54, Poland
Phone : +48 (58) 550 7135
Fax : +48 (58) 551 0484
E-mail : icompolska@icompolska.com.pl
URL : http://www.icompolska.com.pl

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone : +886 (02) 2559 1899
Fax : +886 (02) 2559 1874
E-mail : sales@asia-icom.com
URL : http://www.asia-icom.com

Beijing Icom Ltd.

10C07, Long Silver Mansion, No.88, Yong Ding
Road, Haidian District, Beijing, 100039, China
Phone : +86 (010) 5889 5391/5392/5393
Fax : +86 (010) 5889 5395
E-mail : bjicom@bjicom.com
URL : http://www.bjicom.com

Your local distributor/dealer: