



MF/HF MARINE TRANSCEIVER

IC-M710



Simple, dependable worldwide communications at an affordable price.

1136 channels

160 programmable, 242 ITU SSB duplex, 72 ITU SSB simplex and 662 ITU FSK duplex channels are available.

Rugged construction

The highest quality components are used throughout. Constructed in a die-cast aluminum chassis with surface mount components, the IC-M710 is designed for long hours of operation in the harsh marine environment.

Alphanumeric readout

The large, easy-to-read display shows status at a glance. Seven characters can be programmed into each memory channel to conveniently display station names, ship names, etc.

150 W of output

A full 150 W (PEP) of output power is available for reliable long distance communication. A large cooling fan, in combination with the aluminum chassis, allows continuous transmission at full output power— even during demanding RTTY (radio teletype) and NBDP (narrow band direct printing) operation.

Automatic tuning function

An automatic tuning function is available when using the IC-M710 in combination with the optional AT-140 for quick and easy antenna tuning. Tuning is fully automatic. When you push the PTT on a new frequency, the antenna tuner quickly tunes the antenna automatically.

Easy to use

Two large memory and frequency dials allow quick and easy operation.

And more...

- Covers all allowed bands between 1.6 and 27.5 MHz
- General coverage receiver
- Modes: SSB, RTTY, CW and AM
- RF gain control
- Audio activated squelch
- Terminals for frequency/mode control via NMEA interfacing
- Direct keypad channel selection entry
- Large, front-mounted speaker
- Weather fax ready
- Backlight control
- CW full break-in and semi break-in

SPECIFICATIONS

GENERAL	
• Frequency coverage	: 500kHz–29.9999MHz
Receive	: 1.6– 2.9999, 4.0– 4.9999, 6.0– 6.9999
Transmit	: 8.0– 8.9000, 12.0–13.9999, 16.0–17.9999
	: 18.0–19.9999, 22.0–22.9999, 25.0–27.5000MHz
• Mode	: J3E (USB, LSB), H3E (AM), J2B (AFSK), F1B (FSK), R3E, A1A (CW) (Available modes may differ depending on version)
• Number of channels	: 1136 (max.) (160 programmable; 242 ITU SSB duplex; 72 ITU SSB simplex; 662 ITU FSK duplex)
• Antenna impedance	: 50Ω (nominal)
• Usable temperature range	: –30°C to +60°C (–22°F to +140°F)
Guaranteed temperature	: –20°C to +60°C (–4°F to +140°F)
• Frequency stability	: ±10Hz (below 15MHz) ±20Hz (above 15MHz)
• Power supply requirement	: 13.6V DC ±15% (Negative ground)
• Current drain (at 13.6V DC)	: 2.5A 30A
Receive (Max. audio output)	
Transmit (Max. output power)	
• Dimensions (W×H×D)	: 291.4×116.4×315 mm (Projections not included) 11.47×4.58×12.4 in
• Weight	: 7.8kg; 17.2lb (approx.)

TRANSMITTER	
• Output power	: 150, 60, 20W PEP (selectable) 60, 20W PEP (selectable)
• Spurious emissions	: –62dB (Below peak output power @ 150W pep)
• Carrier suppression	: 40dB (Below peak output power @ 150W pep)
• Unwanted sideband suppression	: 55dB (Below peak output power @ 150W pep with 1500Hz AF Input)
• Microphone impedance	: 600Ω

RECEIVER	
• Sensitivity	: 6.3μV (0.5–1.5999MHz) 1μV (1.6–1.7999MHz) 0.5μV (1.8–29.9999MHz) 32μV (0.5–1.5999MHz) 6.3μV (1.6–1.7999MHz) 3.2μV (1.8–29.9999MHz)
• Spurious response rejection	: More than 70dB (1.6–29.9999MHz)
• Audio output power	: 4.0W at 10% distortion with a 4Ω load
• Audio output impedance	: 4Ω to 8Ω
• Clarity variable range	: ±150Hz

All stated specifications are subject to change without notice or obligation.

Supplied accessories:


- Hand microphone
- DC power cable
- ACC plugs
- Mounting bracket kit
- Microphone hanger
- Speaker plug
- Spare fuses

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.




Matches the transceiver to a long wire antenna with little insertion loss. AT-130 is also available.



Match the transceiver to a dipole antenna. Covers all HF bands from 1.5 to 30 MHz. 8 m×2 antenna wires come attached.



Match the transceiver to a long wire antenna. Covers all HF bands from 1.5 to 30 MHz. 15 m×1 antenna wire comes attached.




Covers from 1.9 to 30 MHz band. Has an SO-239 connector. Easy to assemble (non-kink construction).



Have good shape factor to provide better CW/RTTY reception. Bandwidth: 500Hz/–6 dB



Dynamic microphone. Same as supplied.



10m (32.8ft) shielded control cable connects between AT-140 (or AT-130) and transceiver.

Icom Inc. 1-1-32, Kamiminami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

www.icom.co.jp/world

Count on us!

Icom America Inc.
12421 Willows Road NE,
Kirkland, WA 98034, U.S.A.
Phone: +1 (425) 454-8155
Fax: +1 (425) 454-1509
E-mail: sales@icomamerica.com
URL: http://www.icomamerica.com

Icom (Europe) GmbH
Communication Equipment
Auf der Krautweide 24
65812 Bad Soden am Taunus, Germany
Phone: +49 (6196) 76685-0
Fax: +49 (6196) 76685-50
E-mail: info@icom-europe.com
URL: http://www.icomeurope.com

Icom France s.a.s.
Zac de la Plaine,
1 Rue Brindejonec des Moulinais, BP 45804,
31505 Toulouse Cedex 5, France
Phone: +33 (5) 61 36 03 03
Fax: +33 (5) 61 36 03 00
E-mail: icom@icom-france.com
URL: http://www.icom-france.com

Icom Canada
Glenwood Centre #150-6165
Highway 17A, Delta, B.C.,
V4K 5B8, Canada
Phone: +1 (604) 952-4266
Fax: +1 (604) 952-0090
E-mail: info@icomcanada.com
URL: http://www.icomcanada.com

Icom Spain S.L.
Ctra. Rubi, No. 88 "Edificio Can Castanyer"
Bajos A 08174, Sant Cugat del Valles,
Barcelona, Spain
Phone: +34 (93) 590 26 70
Fax: +34 (93) 589 04 46
E-mail: icom@icomspain.com
URL: http://www.icomspain.com

Icom (Australia) Pty. Ltd.
Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone: +61 (03) 9549 7500
Fax: +61 (03) 9549 7505
E-mail: sales@icom.net.au
URL: http://www.icom.net.au

Icom Brazil
Rua Itororó, 444 Padre Eustáquio
Belo Horizonte MG,
CEP: 30720-450, Brazil
Phone: +55 (31) 3582 8847
Fax: +55 (31) 3582 8987
E-mail: sales@icombrasil.com

Icom (UK) Ltd.
Blacksole House, Altira Park,
Herne Bay, Kent, CT6 6GZ, U.K.
Phone: +44 (0) 1227 741741
Fax: +44 (0) 1227 741742
E-mail: info@icomuk.co.uk
URL: http://www.icomuk.co.uk

Your local distributor/dealer: