

MS marshal

Standby Frequency multifunctional Two-way Radio

MS-5 245MHz

Outstanding Features

- Frequency Standby of working modes: VHF
A/B key : switch Band A or Band B
TDR key: switch dual or single band
- Bright Flashlight Illumination.
Press the side key to turn on the flashlight, it is very convenient for your use when in the dark place.
- Voice prompt.
- Digital FM radio function
Automatic tuning and storing (20 max.) also with frequency display.
You can select from 87-108MHz, almost covers the world radio stations.

Functions

- . Frequency Display Standby
- . VHF working modes
- . Frequency Range: 245MHz (CH01 = 245.000 - CH80 = 245.9875MHz)
- . 80 Number of channels
- . 50 groups CTCSS/105 groups DCS
- . VOX Function
- . High/Low power selection
- . Narrow Bandwidth selection (12.5KHz)
- . Channel Name edit and display
- . Transmit Over Timer
- . Step 12.5K
- . Wire clone function



ACTUAL SIZE

Technical Specification:

Frequency Range	245.000-245.9875MHz
Memory Channels	80 channels
Frequency Stability	+/-2.5ppm
Operating Voltage	7.4V
Operating Temperature	-30°C~+60°C
Antenna Impedance	50Ω
Dimension	58 x 105 x 38(mm)
Weight	250g

Transmitter

Frequency Stability	+/-2.5PPM
RF Carrier Power	VHF: 5W
Max. Frequency Deviation	Channel Space: 12.5KHz +/-2.5KHz
Audio Modulation	+3dB (pre-emphasis by 6dB between 0.3-3KHz)
Adjacent Channel Power	Channel Space: 12.5KHz ≥60 dB

Receiver

Sensitivity (12dB SINAD)	0.16μV
Audio Output power	500mW
Audio Distortion	<5%
Audio Response	(300-3000Hz) +1 to -3dB
Co-channel Rejection	>-8.0dB
Performance of Amplitude Limiter	<3
Adjacent Channel Selection	Channel Space: 12.5KHz >60 dB
Inter-modulation	>65 dB

MS marshal Co.,Ltd.