



VHF P25 CONVENTIONAL & TRUNKED TRANSCEIVER

IC-F9511HT  
IC-F9511HT #100

# High Power Mobile for the First Responder!

P25 Conventional  
& Trunking

AES/DES  
Encryption (Option)

Enhanced  
Vocoder Ready

110W Output Power  
60W Output Power (IC-F9511HT #100)

512 Channels  
128 Zone

Full Dot-matrix  
LCD



Photo includes optional SP-30.

**High-Power** **110W**  
60W 100% DUTY CYCLE for IC-F9511HT #100

# High POWER MOBILE FOR THE FIRST RESPONDER!

Ready for : P25 conventional,  
P25 trunking and  
analog conventional.  
All in one radio!

High-Power **110W**

VHF P25 CONVENTIONAL &  
TRUNKED TRANSCEIVER

**IC-F9511HT** (110W)

**IC-F9511HT # 100** (60W)



## P25 Conventional & Trunking Features



### P25 VHF Conventional and Trunking

The IC-F9511HT comes with P25 VHF conventional and trunking capabilities. You can assign individual channels to analog conventional, P25 conventional or P25 trunking, all within one radio.

### Interoperability

The IC-F9511HT conforms to standard specifications for TIA/EIA -102, CAAB, Digital C4FM Transceiver Performance Recommendations. Provides interoperability with other brand P25 equipment for public safety applications.

### Digital/Analog mixed mode operation

The mixed mode operation allows you to detect and receive both analog FM and P25 digital modes and to transmit either mode depending on programming.

### Individual ID and talkgroup ID

The IC-F9511HT has a 100 individual ID and 250 talkgroup ID memories. Use the display to visually select the person or group you're going to call.

### Optional AES/DES encryption

The IC-F9511HT provides AES and/or DES encryption for secure conversation with the optional UT-125 AES/DES encryption unit or UT-128 DES encryption unit.

### OTAR (Over-the-Air-Rekeying)

The IC-F9511HT supports P25 OTAR for changing encryption keys over the air.

### Enhanced vocoder ready

Using the DVSI's AMBE+2™ vocoder, the IC-F9511HT is enhanced vocoder ready.

### 110W of powerful RF output

A full 110W of output power is available for reliable long distance communication. A large heat sink provides effective cooling mechanism allowing continuous duty cycle operation (20% duty cycle transmission).  
60W 100% Duty Cycle for IC-F9511HT#100

### Compact "letter size" RF unit

While the IC-F9511HT provides 110W of RF output, the RF (main) unit dimensions are only 175 (W) × 60 (H) × 279 (D) mm (6 $\frac{7}{8}$  × 2 $\frac{3}{8}$  × 10 $\frac{1}{2}$  in), so the RF unit can be fit into a "letter size" console box.

### IP54 dust and water resistance

The controller and RF unit have dust-protection and splash resistance, equivalent to IP54.

### Dot matrix, multi-function LCD

With a high contrast dot matrix display, upper and lower case characters can be easily distinguished. The display shows 12 characters by 2 lines. LCD backlight is standard.



Internal clock setting example

### Self-grounding mic, HM-148G

The supplied HM-148G self-grounding microphone has a mechanism for self grounding where a grounding wire is no longer required.

### Tactical group function

The tactical group function allows you to copy memory channels to the tactical zone and temporarily regroup memory channels. Using the optional zone copy cable, memory channels in the tactical zone can be transferred from a master radio to other radios.

### Abundant scanning functions

The dual priority scan monitors two primary channels alternately, while scanning other channels. The mode dependent scan function automatically changes the scan list according to the operating channel setting. The talk back function with timer beep, TX channel and cancel channel settings allow you to preset the transmission channel when you push the PTT button during a scanning operation or cancel the scanning.

### Radio stun/kill and Power-on password function

The radio stun/kill function\* disables a lost or stolen radio over the air, eliminating security threats from undesired listeners. The power-on password prevents unauthorized people from turning on the radio.

\* P25 digital mode only.

### Optional external speaker SP-30

Newly designed external speaker, SP-30 offers 15W\* (typ.) of high level audio with the IC-F9511HT for improved operation in noisy environments.

\* Rated input of the SP-30 is 20W.

### Other features

- Wide frequency coverage (136–174MHz)
- FM wide/narrow channel spacing\*<sup>1</sup>
- Built-in audio compander\*<sup>1</sup>
- Built-in inversion type voice scrambler\*<sup>1</sup>
- NTIA VHF specification compliant
- Talk around function
- DTMF autodial\*<sup>1</sup>
- Microphone hanger action (On hook scan and off hook monitor)
- 2-Tone encoder and decoder\*<sup>1</sup> and MDC 1200 compatible\*<sup>1</sup> (Available in future)

\*<sup>1</sup> Analog mode only



Optional external speaker, SP-30

### Separate controller

The controller and speaker are separated from the RF unit for flexible installation. A 5m (16.4ft) separation cable is attached to the controller and optional separation cable length is selectable from 1.9m (6.2ft), 3m (9.8ft) and 8m (26.2ft).

### 512 memory channels, 128 zones

Up to 512 memory channels can be divided into 128 memory zones, allowing you flexible channel and communication group management. The CTCSS and DTCS encoder and decoder\* are also built-in to set up your own talk groups. \* Analog mode only.

### 9-pin external speaker connector

The IC-F9511HT has a 9-pin speaker connector with a 15W (typ.) audio amplifier for connecting the SP-30 external speaker, horn honk and ignition sensing line, etc.. When an external loud speaker is connected, the RX speaker function allows you to relay the received audio over the loud speaker.

### Programmable accessory connector

The IC-F9511HT has a D-SUB 25-pin ACC connector for connecting external devices. It has reserved pins for programming to input operating channels, turn on/off functions and output received audio.



## SPECIFICATIONS

### GENERAL

- Frequency range : 136-174MHz
- Number of channels : Max. 512 channels/  
128 zones
- Channel spacing : 12.5/25kHz (IC-F9511HT#100)  
: 15/30kHz (analog)
- PLL channel step : 2.5kHz, 3.125kHz
- Antenna impedance : 50Ω (SO-239)
- Operating Temp. range : -30°C to +60°C  
: -22°F to +140°F
- Power supply requirement : 13.6V DC nominal
- Current drain (approx) :
 

TX	High (110W)	22.0A
	(60W)	15.0A
Rx	Max. audio	3.0A
	Stand-by	400mA
- Dimensions (W×H×D) (projections not included) :
 

RF unit	175×60×279 mm ; 6 <sup>7</sup> / <sub>8</sub> × 2 <sup>3</sup> / <sub>8</sub> × 10 <sup>3</sup> / <sub>32</sub> in
Controller	178×48×50 mm ; 7 × 1 <sup>7</sup> / <sub>8</sub> × 1 <sup>3</sup> / <sub>32</sub> in
- Weight (approx.) : 4.1kg; 9.0lb  
With controller & cable 4.7kg; 10.4lb

Measurements made in accordance with TIA-102 (Digital), TIA-603B (Wide/narrow). All stated specifications are subject to change without notice or obligation.

### TRANSMITTER

- Output power (approx) : 110W  
60W (IC-F9511HT#100)
- Max. frequency deviation : ±5.0/2.5kHz (Wide/Narrow)  
Maximum pattern ±2.85kHz (Digital)
- Frequency error : ±1.0ppm
- Spurious emissions : 80dB
- Adjacent channel power : 80/70dB (Wide/Narrow)  
70dB (Digital)
- FM hum and noise : 60/55dB (Wide/Narrow)
- Audio harmonic distortion : 3% deviation
- Ext. microphone impedance : 600Ω (8-pin modular)

### Applicable U.S. Military Specifications & IP Rating

Standard	MIL 810 F	
	Method	Procedure
Low Pressure	500.4	I, II
High Temperature	501.4	I, II
Low Temperature	502.4	I, II
Temperature Shock	503.4	I
Solar Radiation	505.4	I
Rain	506.4	I, III
Humidity	507.4	-
Salt Fog	509.4	-
Dust	510.4	I
Vibration	514.5	I
Shock	516.5	I, IV

Also meets equivalent MIL-STD-810-C, -D and -E.

Ingress Protection Standard	
Dust & Water	IP54 (Dust-protection and water resistant)

### RECEIVER

- Sensitivity :
 

Analog	0.25μV (at 12dB SINAD)
Digital	0.25μV (at 5% BER)
- Squelch sensitivity : 0.25μV (at threshold)
- Adjacent Ch. selectivity :
 

Analog	85/80dB
Digital	65dB
- Spurious response : 90dB
- Intermodulation : 85dB
- Hum and noise ratio : 55/51dB (Wide/Narrow)  
52dB (Digital)
- Audio output power : 15W at 3% distortion  
(with external speaker) with a 4Ω load

### Supplied Accessories

- Hand microphone, HM-148G
- Separation cable, 5m (16.4ft)
- Microphone hanger
- Mounting bracket kit for main unit and controller
- Fuse
- Cable with fuse holder
- Controller unit
- DC power cable
- Key assign stickers
- Socket terminals
- Crimp terminals
- Speaker is an option.

## OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.

### HAND MICROPHONES



- HM-152 : Regular hand microphone.
- HM-152T : DTMF microphone.
- HM-148G : Heavy duty microphone. Self-grounding type. Same as supplied.
- HM-148T : Heavy duty microphone with DTMF keypad. Self-grounding type.

### DESKTOP MICROPHONE



Convenient for dispatching, equipped with monitor switch.

### EXTERNAL SPEAKER



20W rated input power (40W max. input).

### ENCRYPTION UNITS



- UT-125 : Provides AES and DES encryption capabilities.
- UT-128 : Provides DES encryption capabilities.

### SEPARATION CABLES



- OPC-609 : 1.9m; 6.2ft separation cable.
- OPC-607 : 3.0m; 9.8ft separation cable.
- OPC-726 : 5.0m; 16.4ft separation cable. Same as supplied.
- OPC-608 : 8.0m; 26.2ft separation cable.

### ZONE COPY CABLES



- OPC-1532 : Mobile to mobile zone copy cable.
- OPC-1871 : Mobile to handheld zone copy cable.

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia and/or other countries. AMBE+2 is a trademark and property of Digital Voice Systems Inc. All other trademarks are the properties of their respective holders.

## Icom Inc.

1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 URL: <http://www.icom.co.jp/world/index.html>

## Count on us!

### Icom America Inc.

2380 116th Avenue NE,  
Bellevue, WA 98004, U.S.A.  
Phone : +1 (425) 454-8155  
Fax : +1 (425) 454-1509  
E-mail : [sales@icomamerica.com](mailto:sales@icomamerica.com)  
URL : <http://www.icomamerica.com>

### Icom New Zealand

146A Harris Road, East Tamaki,  
Auckland, New Zealand  
Phone : +64 (09) 274 4062  
Fax : +64 (09) 274 4708  
E-mail : [inquiries@icom.co.nz](mailto:inquiries@icom.co.nz)  
URL : <http://www.icom.co.nz>

### Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay,  
Kent, CT6 8LD, U.K.  
Phone : +44 (0)1227 741741  
Fax : +44 (0)1227 741742  
E-mail : [info@icomuk.co.uk](mailto:info@icomuk.co.uk)  
URL : <http://www.icomuk.co.uk>

### Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,  
Taipei, Taiwan, R.O.C.  
Phone : +886 (02) 2559 1899  
Fax : +886 (02) 2559 1874  
E-mail : [sales@asia-icom.com](mailto:sales@asia-icom.com)  
URL : <http://www.asia-icom.com>

Your local distributor/dealer:

### Icom Canada

Glenwood Centre #150-6165 Highway 17,  
Delta, B.C., V4K 5B8, Canada  
Phone : +1 (604) 952-4266  
Fax : +1 (604) 952-0090  
E-mail : [info@icomcanada.com](mailto:info@icomcanada.com)  
URL : <http://www.icomcanada.com>

### Icom (Europe) GmbH

Communication Equipment  
Himmelgeister Str. 100,  
D-40225 Düsseldorf, Germany  
Phone : +49 (0211) 346047  
Fax : +49 (0211) 333639  
E-mail : [info@icom-europe.com](mailto:info@icom-europe.com)  
URL : <http://www.icomeurope.com>

### Icom France s.a.s.

Zac de la Plaine,  
1 Rue Brindejonn des Moulins, BP 45804,  
31505 Toulouse Cedex 5, France  
Phone : +33 (5) 61 36 03 03  
Fax : +33 (5) 61 36 03 00  
E-mail : [icom@icom-france.com](mailto:icom@icom-france.com)  
URL : <http://www.icom-france.com>

### Beijing Icom Ltd.

10C07, Long Silver Mansion, No.88, Yong Ding  
Road, Haidian District, Beijing, 100039, China  
Phone : +86 (010) 5889 5391/5392/5393  
Fax : +86 (010) 5889 5395  
E-mail : [bjicom@bjicom.com](mailto:bjicom@bjicom.com)  
URL : <http://www.bjicom.com>

### Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,  
Clayton, VIC 3168 Australia  
Phone : +61 (03) 9549 7500  
Fax : +61 (03) 9549 7505  
E-mail : [sales@icom.net.au](mailto:sales@icom.net.au)  
URL : <http://www.icom.net.au>

### Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"  
Bajos A 08174, Sant Cugat del Valles,  
Barcelona, Spain  
Phone : +34 (93) 590 26 70  
Fax : +34 (93) 589 04 46  
E-mail : [icom@icomspain.com](mailto:icom@icomspain.com)  
URL : <http://www.icomspain.com>

### Icom Polska

81-850 Sopot, ul. 3 Maja 54, Poland  
Phone : +48 (58) 550 7135  
Fax : +48 (58) 551 0484  
E-mail : [icompolkska@icompolkska.com.pl](mailto:icompolkska@icompolkska.com.pl)  
URL : <http://www.icompolkska.com.pl>